



# TYPE RXLSK AC REVERSING STARTERS 3 PHASE FULL VOLTAGE



All Starters Supplied with BUILT-IN HEATERS

Size 00-2



NEMA RATED

AC-1 AMPS	AC-3 AMPS	Horse Power (UL) Ratings 3 Phase Motor Max UL HP	OPEN	ENCLOSED					Comparable NEMA HP NEMA Size
				NEMA 1 General Purpose	NEMA 4X Outdoor (non-metal)	NEMA 4 (metal)	NEMA 3R (metal)	NEMA 12 Dust Tight (metal)	
20A	9A	200V 3 HP 230V 3 HP 460V 5 HP 600V 5 HP	RXLS05 -*0-*	RXLS05 -*1-*	RXLS05 -*4x-*	RXLS05 -*4-*	RXLS05 -*3R-*	RXLS05 -*12-*	
			\$171	\$243	\$296	\$316	\$277	\$306	
25A	9A	200V 3 HP 230V 3 HP 460V 5 HP 600V 7.5 HP LIST	RXLS4K -*0-*	RXLS4K -*1-*	RXLS4K -*4x-*	RXLS4K -*4-*	RXLS4K -*3R-*	RXLS4K -*12-*	
			\$238	\$328	\$394	\$437	\$375	\$427	
25A	12A	200V 3 HP 230V 3 HP 460V 7.5 HP 600V 10 HP LIST	RXLS5K -*0-*	RXLS5K -*1-*	RXLS5K -*4x-*	RXLS5K -*4-*	RXLS5K -*3R-*	RXLS5K -*12-*	200V 1.5 HP 230V 1.5 HP 460V 2 HP 600V 2 HP NEMA 00
			\$262	\$352	\$418	\$451	\$398	\$441	
32A	18A	200V 5 HP 230V 5 HP 460V 10 HP 600V 15 HP LIST	RXLS7K -*0-*	RXLS7K -*1-*	RXLS7K -*4x-*	RXLS7K -*4-*	RXLS7K -*3R-*	RXLS7K -*12-*	
			\$268	\$358	\$424	\$465	\$412	\$455	
45A	25A	200V 5 HP 230V 7.5 HP 460V 15 HP 600V 15 HP LIST	RXLS11K -*0-*	RXLS11K -*1-*	RXLS11K -*4x-*	RXLS11K -*4-*	RXLS11K -*3R-*	RXLS11K -*12-*	200V 3 HP 230V 3 HP 460V 5 HP 600V 5 HP NEMA 0
			\$298	\$388	\$454	\$499	\$424	\$489	
60A	32A	200V 10 HP 230V 10 HP 460V 20 HP 600V 25 HP LIST	RXLS15K -*0-*	RXLS15K -*1-*	RXLS15K -*4x-*	RXLS15K -*4-*	RXLS15K -*3R-*	RXLS15K -*12-*	
			\$388	\$478	\$544	\$608	\$568	\$598	
60A	40A	200V 10 HP 230V 10 HP 460V 25 HP 600V 25 HP LIST	RXLS18K -*0-*	RXLS18K -*1-*	RXLS18K -*4x-*	RXLS18K -*4-*	RXLS18K -*3R-*	RXLS18K -*12-*	200V 7.5 HP 230V 7.5 HP 460V 10 HP 600V 10 HP NEMA 1
			\$408	\$498	\$564	\$750	\$705	\$740	
90A	50A	200V 15 HP 230V 15 HP 460V 30 HP 600V 40 HP LIST	RXLS22K -*0-*	RXLS22K -*1-*	RXLS22K -*4x-*	RXLS22K -*4-*	RXLS22K -*3R-*	RXLS22K -*12-*	
			\$438	\$633	\$713	\$985	\$784	\$975	
110A	65A	200V 20 HP 230V 20 HP 460V 40 HP 600V 50 HP LIST	RXLS30K -*0-*	RXLS30K -*1-*	RXLS30K -*4x-*	RXLS30K -*4-*	RXLS30K -*3R-*	RXLS30K -*12-*	
			\$609	\$804	\$884	\$1,170	\$897	\$1,160	
110A	80A	200V 20 HP 230V 25 HP 460V 50 HP 600V 60 HP LIST	RXLS37K -*0-*	RXLS37K -*1-*	RXLS37K -*4x-*	RXLS37K -*4-*	RXLS37K -*3R-*	RXLS37K -*12-*	200V 10 HP 230V 15 HP 460V 25 HP 600V 25 HP NEMA 2
			\$709	\$904	\$984	\$1,255	\$982	\$1,245	

**Steps To Order Motor Starter:**

**Step 1-Size** Choose from the UL HP and Voltage list per your application.  
For example: 5 HP 230V 3 phase part # RXLS7K.

**Step 2 - Coil\*** From the coil suffix chart on the next page choose the suffix for your control circuit voltage requirement.(Example: 24VAC = G-) (Part #RXLS7K-G)

**Step 3 -Enclosure** specify "open" or "enclosed" requirements.  
For example if NEMA 12 (part #RXLS7K-G12-).

**Step 4 -Overload Amps\*\*** This step requires a suffix for your overload protection, refer to "OVERLOAD RELAY SUFFIX TABLE" (next page)  
(Example: 5HP @ 230V 3 Phase, if 13 Full Load Amps = suffix "N".)  
Example: RXLS7K- G12 - N

**RXLSK Series Starters**

- (what's included?)
- AEG 3 Phase Reversing Starters.
- (Ambient compensated Bi metallic windings).
- -25°C - +60°C (-11.20°F - +140°F).
- Overload Class 10 (adjustable heaters).
- Electrical & Mechanical interlocks as standard.
- Thru door reset. Enclosed units only).

Modifications and accessories are listed on pages 60, 61

For Operators, Transformers & Accessories see page 60