



# TYPE XLSK AC MOTOR STARTERS

## 3 Phase Full Voltage-Across the Line



All Starters Supplied with BUILT-IN HEATERS Size 00-2 CE NEMA RATED

UL General purpose Amp	NEMA Rated	Horse Power (UL) Ratings 3 Phase Motor Max UL HP	Volts	OPEN	ENCLOSED					NEMA HP ★
					NEMA 1 General Purpose	NEMA 4X Outdoor (non-metal)	NEMA 4 (metal)	NEMA 3R (metal)	NEMA 12 Dust Tight (metal)	
		200V 3 HP 230V 3 HP 460V 5 HP		XLS05 -★0-★★ \$89	XLS05 -★1-★★ \$161	XLS05 -★4x-★★ \$184	XLS05 -★4-★★ \$190	XLS05 -★3R-★★ \$170	XLS05 -★12-★★ \$170	★ See Below
25A	00	200V 3 HP 230V 3 HP 460V 7.5 HP 600V 10 HP LIST		XLS5K -★0-★★ \$142	XLS5K -★1-★★ \$216	XLS5K -★4x-★★ \$267	XLS5K -★4-★★ \$287	XLS5K -★3R-★★ \$247	XLS5K -★12-★★ \$247	200V 1.5 HP 230V 1.5 HP 460V 2 HP 600V 2 HP NEMA 00
32A		200V 5 HP 230V 5 HP 460V 10 HP 600V 15 HP LIST		XLS7K -★0-★★ \$145	XLS7K -★1-★★ \$217	XLS7K -★4x-★★ \$270	XLS7K -★4-★★ \$290	XLS7K -★3R-★★ \$250	XLS7K -★12-★★ \$250	
45A	0	200V 5 HP 230V 7.5 HP 460V 15 HP 600V 15 HP LIST		XLS11K -★0-★★ \$170	XLS11K -★1-★★ \$242	XLS11K -★4x-★★ \$295	XLS11K -★4-★★ \$315	XLS11K -★3R-★★ \$275	XLS11K -★12-★★ \$275	200V 3 HP 230V 3 HP 460V 5 HP 600V 5 HP NEMA 0
54A		200V 10 HP 230V 10 HP 460V 20 HP 600V 25 HP LIST		XLS15K -★0-★★ \$210	XLS15K -★1-★★ \$282	XLS15K -★4x-★★ \$335	XLS15K -★4-★★ \$355	XLS15K -★3R-★★ \$315	XLS15K -★12-★★ \$315	
55A	1	200V 10 HP 230V 10 HP 460V 25 HP 600V 25 HP LIST		XLS18K -★0-★★ \$250	XLS18K -★1-★★ \$322	XLS18K -★4x-★★ \$380	XLS18K -★4-★★ \$400	XLS18K -★3R-★★ \$355	XLS18K -★12-★★ \$355	200V 7.5 HP 230V 7.5 HP 460V 10 HP 600V 10 HP NEMA 1
80A		200V 15 HP 230V 15 HP 460V 30 HP 600V 40 HP LIST		XLS22K -★0-★★ \$275	XLS22K -★1-★★ \$365	XLS22K -★4x-★★ \$427	XLS22K -★4-★★ \$447	XLS22K -★3R-★★ \$389	XLS22K -★12-★★ \$389	
100A		200V 20 HP 230V 20 HP 460V 40 HP 600V 50 HP LIST		XLS30K -★0-★★ \$343	XLS30K -★1-★★ \$433	XLS30K -★4x-★★ \$499	XLS30K -★4-★★ \$690	XLS30K -★3R-★★ \$488	XLS30K -★12-★★ \$499	
110A	2	200V 20 HP 230V 25 HP 460V 50 HP 600V 60 HP LIST		XLS37K -★0-★★ \$407	XLS37K -★1-★★ \$497	XLS37K -★4x-★★ \$563	XLS37K -★4-★★ \$780	XLS37K -★3R-★★ \$540	XLS37K -★12-★★ \$540	200V 10 HP 230V 15 HP 460V 25 HP 600V 25 HP NEMA 2

Modifications and accessories are listed on pages 60, 61.

### Steps To Order Motor Starter:

**Step 1-Size** Choose from the UL HP and Voltage list per your application.  
For example: 5 HP 230V 3 phase part # XLS7K.

**Step 2 - Coil\*** From the coil suffix chart on the next page choose the suffix for your control circuit voltage requirement.(Example: 24VAC = G-) (Part # XLS7K-G)

**Step 3 -Enclosure** specify "open" or "enclosed" requirements.  
For example if NEMA 12 (part # XLS7K-G12-).

**Step 4 -Overload Amps\*\*** This step requires a suffix for your overload protection, refer to "OVERLOAD RELAY SUFFIX TABLE"  
(Example: 5HP @ 230V 3 Phase,if 13 Full Load Amps = suffix "N".)  
Example: XLS7K - G12 - N

** Overload Relay Suffix			
O.L. Relay Setting Range		O.L. Relay Setting Range	
Suffix	(Amps)	Suffix	(Amps)
-B	0.16-0.26	-ON	21-26
-C	0.25-0.41	-P	25-32
-D	0.4-0.65	-Q	30-40
-E	0.65-1.1	-QN	42-55
-F	1.1-1.5	-RN	54-65
-G	1.3-1.9	-SN	64-82
-H	1.8-2.7	-TM	78-97
-I	2.5-4	-TN	90-110
-K	4-6.3	-TT	110-140
-L	5.5-8.5	-U	140-190
-M	8-12	-V	175-280
-N	10-16	-W	200-310
-O	14.5-18	-WT	250-400
-OM	17.5-22	-X	315-500
		-Y	430-700